



PRODUCT-DETAILS

XT5N 400 Ekip Dip LS/I In=400 3p F F

XT5N 400 Ekip Dip LS/I In=400 3p F F



General Information	
Extended Product Type:	XT5N 400 Ekip Dip LS/I In=400 3p F F
Product ID:	1SDA100354R1
EAN:	8056221004312
Catalog Description:	XT5N 400 Ekip Dip LS/I In=400 3p F F
Long Description:	C.BREAKER TMAX XT5N 400 FIXED THREE-POLE WITH FRONT TERMINALS AND SOLID-STATE RELEASE IN AC EKIP DIP LS/I R 400
Display Name:	XT5N 400 Ekip Dip LS/I In=400 3p F F

ABB EcoSolutions	
ABB EcoSolutions:	Yes
ABB Site Meeting Group Waste To Landfill Target:	UL 2799 Zero Waste To Landfill Validation available
End Of Life Disassembling Instructions:	9AKK108468A2354
Environmental Product Declaration - EPD:	9AKK108468A1899 9AKK108468A9748
Extended Product Lifetime:	Product Modularity

Recyclability Rate of the Product acc. to EN45555: Design for Closing Resource Loops - Standard EN45555 - 61.8 %

Material Compliance

REACH Declaration:	9AKK108466A1425
RoHS Declaration:	9AKK108466A1424
RoHS Information:	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019
Conflict Minerals Reporting Template (CMRT):	9AKK108467A5658
Toxic Substances Control Act - TSCA:	9AKK108467A8326
SCIP:	e30e371e-cec8-4cc8-9129-d0a36ec71e8e Italy
Simplified SCIP:	a1a85500-d067-4e44-b55c-4333c812c1c6 Czechia f02a5d57-a01f-4159-a134-b8ae7cc3fdce Croatia 748dc61e-8473-4d87-9280-e2f1f5971578 Poland ebc4ad00-0c15-4610-b8b1-7fc26a089fbc Netherlands 2c741dba-a4ae-4d06-95bb-0fa1293da446 Belgium 492d38f5-0d42-4317-aa8b-97a6d4096e4d Germany 3659ddb-6559-4dd4-9de6-f05f63612ae4 Poland 9dafc898-b2d7-4bd9-aa99-94b8f23f0c6c Germany 124ffc7f-89c0-42f8-ad98-2d1b34611bf6 Germany 1f5df668-ad98-4f19-a7f1-de67da0c0a16 Denmark 7a52c1aa-81c2-453e-a12f-8e3059f74038 Poland b80fb322-a53a-4ea4-9cf9-d5e935a29471 France 8ed1307b-c937-4c70-92ea-96be64ca513c Sweden d56a7e48-9efb-44a0-9b56-7e0dd1a64a47 Germany 9c0dcb51-7dad-4fcc-b536-5986a5212902 Sweden c9b2af46-31fd-40ca-875e-d85eb761f0a6 Hungary 21f0ee32-2cb1-4d70-ab77-d0bdfa0a761c Norway 14a0a9d0-cf49-48f0-8469-0789e2a283d1 Finland a3006f4e-c822-48ab-8cad-0225096e1054 Greece 904658a9-bba4-48b4-9379-4a42f8c01004 Estonia 56fdaf13-1fe5-4ef5-8fdf-2c0d48f6eeb8 Bulgaria 439ad23d-209b-48eb-b077-146de1ce787c Portugal 8f16a030-4984-49e2-a0a8-6637ae9df31b Belgium a3c2f2aa-9bd4-4e50-91d8-8e115ec33be4 Spain fe376336-d573-4e41-b53c-0a4d90afbff7 France 1e149fc1-02b2-422e-aa1d-525cb47c80c4 Germany 3475bdf-8bb0-446e-86f6-7bf0dfbf6c25 Hungary

Environmental

Environmental Information:	9AKK108467A6707
-----------------------------------	-----------------

Ordering

Order Code US and Canada:	XT5NE340AEFF000XXX
E-Number (Finland):	3641307
E-Number (Norway):	4380249
EAN:	8056221004312
Minimum Order Quantity:	1 piece
Customs Tariff Number:	85362090

Dimensions

Product Net Width:	140 mm
Product Net Height:	205 mm
Product Net Depth / Length:	103.5 mm
Product Net Weight:	4.82 kg

Container Information

Package Level 1 Units:	box 1 piece
Package Level 1 Width:	250 mm
Package Level 1 Height:	245 mm
Package Level 1 Depth / Length:	285 mm
Package Level 1 Gross Weight:	5.308 kg
Package Level 1 EAN:	8056221004312

Additional Information

Circuit Breaker Type to be Associated:	Power Distribution
Product Main Type:	SACE Tmax XT
Product Name:	Moulded Case Circuit Breaker
Product Type:	Automatic Circuit Breaker
Version:	F
CAD Dimensional Drawing:	1SDH002065A1115 1SDH002065A1131

Technical

Current Type:	AC
Electrical Durability:	7000 cycle 60 cycles per hour
Mechanical Durability:	20000 cycle 120 cycles per hour
Number of Poles:	3P
Order Multiple:	1 piece
Power Loss:	19 W
Rated Current (I_n):	400 A
Rated Impulse Withstand Voltage (U_{imp}):	8 kV
Rated Insulation Voltage (U_i):	1000 V
Rated Operational Voltage:	690 V AC

Rated Service Short-Circuit Breaking Capacity (I_{cs}):	(220 V AC) 70 kA (230 V AC) 70 kA (240 V AC) 70 kA (380 V AC) 36 kA (415 V AC) 36 kA (440 V AC) 36 kA (500 V AC) 25 kA (525 V AC) 25 kA (690 V AC) 20 kA
Rated Short-time Withstand Current Low Voltage (I_{cw}):	5 kA
Rated Ultimate Short-Circuit Breaking Capacity (I_{cu}):	(220 V AC) 70 kA (230 V AC) 70 kA (240 V AC) 70 kA (380 V AC) 36 kA (415 V AC) 36 kA (440 V AC) 36 kA (500 V AC) 25 kA (525 V AC) 25 kA (690 V AC) 20 kA
Rated Uninterrupted Current (I_u):	400 A
Release:	Ekip Dip LS/I
Release Type:	EL
Short-Circuit Performance Level:	N
Standards:	IEC60947-2
Sub-type:	XT5
Terminal Connection Type:	Front

Certificates and Declarations

Data Sheet, Technical Information:	1SDC210100D0206 1SDC210099D0206
Declaration of Conformity - CE:	9AKK107680A2824
EU Data Act Compliance Declaration:	1SDH002560A1001
Mechanical Drawings:	1SDH002011A1101
Wiring Diagram:	1SDM000005A1001
Instructions and Manuals:	1SDH002011A1001

External Classifications and Standards

ETIM 9:	EC000228 - Power circuit-breaker for trafo/generator/installation protection
ETIM 10:	EC000228 - Power circuit-breaker for trafo/generator/installation protection
Object Classification Code:	Q
WEEE Category:	5. Small Equipment (No External Dimension More Than 50 cm)
eClass:	V11.1 : 27370409

Accessories

Identifier	Description	Type	Qty	Unit Of Measure
------------	-------------	------	-----	-----------------

1SDA104821R1	AUE XT5-XT6 F/P 2 CONTACTS IN CH x RHx	AUE XT5-XT6 F/P 2 CONTACTS IN CH x RHx	1	piece
1SDA104822R1	AUE XT5-XT6 W 2 CONTACTS IN CH x RHx	AUE XT5-XT6 W 2 CONTACTS IN CH x RHx	1	piece
1SDA104814R1	AUP BOX for FP XT5	AUP BOX for FP XT5	1	piece
1SDA104784R1	AUX-C 1Q + 1SY 400V AC/DC XT5 F/P	AUX-C 1Q + 1SY 400V AC/DC XT5 F/P	1	piece
1SDA104785R1	AUX-C 1Q + 1SY 400V AC/DC XT5 W	AUX-C 1Q + 1SY 400V AC/DC XT5 W	1	piece
1SDA104786R1	AUX-C 1Q + 1SY L 24V DC XT5 F/P	AUX-C 1Q + 1SY L 24V DC XT5 F/P	1	piece
1SDA104787R1	AUX-C 1Q + 1SY L 250V AC/DC XT5 F/P	AUX-C 1Q + 1SY L 250V AC/DC XT5 F/P	1	piece
1SDA104788R1	AUX-C 1Q+1SY 24VDC XT5-XT6 W	AUX-C 1Q+1SY 24VDC XT5-XT6 W	1	piece
1SDA104789R1	AUX-C 1Q+1SY 250V AC/DC XT5-XT6 W	AUX-C 1Q+1SY 250V AC/DC XT5-XT6 W	1	piece
1SDA104790R1	AUX-C 1S51 24VdC XT5-XT6 W	AUX-C 1S51 24VdC XT5-XT6 W	1	piece
1SDA104791R1	AUX-C 1S51 250V AC/dC XT5-XT6 W	AUX-C 1S51 250V AC/dC XT5-XT6 W	1	piece
1SDA104792R1	AUX-C 1S52 24VdC XT5-XT6 W	AUX-C 1S52 24VdC XT5-XT6 W	1	piece
1SDA104793R1	AUX-C 1S52 250V AC/dC XT5-XT6 W	AUX-C 1S52 250V AC/dC XT5-XT6 W	1	piece
1SDA104794R1	AUX-C 2Q 400V AC/DC XT5 W	AUX-C 2Q 400V AC/DC XT5 W	1	piece
1SDA104795R1	AUX-C 2Q 400V AC/DC XT5 F/P	AUX-C 2Q 400V AC/DC XT5 F/P	1	piece
1SDA104796R1	AUX-C 2Q+1SY 250V AC/CC XT5-XT6 W	AUX-C 2Q+1SY 250V AC/CC XT5-XT6 W	1	piece
1SDA104797R1	AUX-C 3Q+1SY 24VDC XT5-XT6 W	AUX-C 3Q+1SY 24VDC XT5-XT6 W	1	piece
1SDA104798R1	AUX-C 3Q+1SY 250V AC XT5-XT6 W	AUX-C 3Q+1SY 250V AC XT5-XT6 W	1	piece
1SDA104799R1	AUX-C 1S52 24VDC XT5-XT6 F/P	AUX-C 1S52 24VDC XT5-XT6 F/P	1	piece
1SDA104800R1	AUX-C 1S52 250V AC/DC XT5-XT6 F/P	AUX-C 1S52 250V AC/DC XT5-XT6 F/P	1	piece
1SDA104871R1	FLD - XT5 F/P	FLD - XT5 F/P	1	piece
1SDA104872R1	FLD - XT5 W	FLD - XT5 W	1	piece
1SDA105061R1	KLC XT5-XT6 K.L.RONIS SE.O/C1228 xCB	KLC XT5-XT6 K.L.RONIS SE.O/C1228 xCB	1	piece
1SDA105062R1	KLC XT5-XT6 KE.LO. RONIS EQ.A 1228 OPxB	KLC XT5-XT6 KE.LO. RONIS EQ.A 1228 OPxB	1	piece
1SDA105063R1	KLC XT5-XT6 KE.LO. RONIS EQ.B 1228 OPxB	KLC XT5-XT6 KE.LO. RONIS EQ.B 1228 OPxB	1	piece
1SDA105064R1	KLC XT5-XT6 KE.LO. RONIS EQ.C 1228 OPxB	KLC XT5-XT6 KE.LO. RONIS EQ.C 1228 OPxB	1	piece
1SDA105065R1	KLC XT5-XT6 KE.LO. RONIS EQ.D 1228 OPxB	KLC XT5-XT6 KE.LO. RONIS EQ.D 1228 OPxB	1	piece
1SDA105066R1	KLC XT5-XT6 KE.LO. RONIS SE.1228 xCB	KLC XT5-XT6 KE.LO. RONIS SE.1228 xCB	1	piece

1SDA105067R1	KLC-A Key lock open Kirk XT5-XT6	KLC-A Key lock open Kirk XT5-XT6	1	piece
1SDA105068R1	KLC-A Key lock open RONIS 1104 XT5-XT6	KLC-A Key lock open RONIS 1104 XT5-XT6	1	piece
1SDA105069R1	KLC-A Key lock open STI XT5-XT6	KLC-A Key lock open STI XT5-XT6	1	piece
1SDA105109R1	KL-D RONIS FP W XT5-XT6 KEY LO. SEV.1228	KL-D RONIS FP W XT5-XT6 KEY LO. SEV.1228	1	piece
1SDA105112R1	KL-D GIUSSANI FP W XT5-XT6 KEY LO.EQ.	KL-D GIUSSANI FP W XT5-XT6 KEY LO.EQ.	1	piece
1SDA105113R1	KL-S GIUSSANI FP W XT5-XT6 KEY LO.EQ.	KL-S GIUSSANI FP W XT5-XT6 KEY LO.EQ.	1	piece
1SDA105114R1	KL-S RONIS FP W XT5-XT6 KEY LO.EQ.1228 A	KL-S RONIS FP W XT5-XT6 KEY LO.EQ.1228 A	1	piece
1SDA105080R1	RHL XT5-XT6 K.L.RONIS SE.O/C1228 RHx/FLD	RHL XT5-XT6 K.L.RONIS SE.O/C1228 RHx/FLD	1	piece
1SDA105081R1	RHL XT5-XT6 KE.LO. RONIS SE.1228 RHx/FLD	RHL XT5-XT6 KE.LO. RONIS SE.1228 RHx/FLD	1	piece
1SDA105082R1	RHL XT5-XT6K.LO.RONIS EQ.FEL.A1228RHxFLD	RHL XT5-XT6K.LO.RONIS EQ.FEL.A1228RHxFLD	1	piece
1SDA105083R1	RHL XT5-XT6K.LO.RONIS EQ.FEL.B1228RHxFLD	RHL XT5-XT6K.LO.RONIS EQ.FEL.B1228RHxFLD	1	piece
1SDA105084R1	RHL XT5-XT6K.LO.RONIS EQ.FEL.C1228RHxFLD	RHL XT5-XT6K.LO.RONIS EQ.FEL.C1228RHxFLD	1	piece
1SDA105085R1	RHL XT5-XT6K.LO.RONIS EQ.FEL.D1228RHxFLD	RHL XT5-XT6K.LO.RONIS EQ.FEL.D1228RHxFLD	1	piece
1SDA104879R1	MOE XT5 24V DC Auto-Reset	MOE XT5 24V DC Auto-Reset	1	piece
1SDA104881R1	MOE XT5 48...60V DC Auto-Reset	MOE XT5 48...60V DC Auto-Reset	1	piece
1SDA104883R1	MOE XT5 110...125V AC/DC Auto-Reset	MOE XT5 110...125V AC/DC Auto-Reset	1	piece
1SDA104885R1	MOE XT5 220...250V AC/DC Auto-Reset	MOE XT5 220...250V AC/DC Auto-Reset	1	piece
1SDA104887R1	MOE XT5 380V AC Auto-Reset	MOE XT5 380V AC Auto-Reset	1	piece
1SDA104899R1	MOE-E XT5 24V DC	MOE-E XT5 24V DC	1	piece
1SDA104901R1	MOE-E XT5 48...60V DC	MOE-E XT5 48...60V DC	1	piece
1SDA104903R1	MOE-E XT5 110...125V AC/DC	MOE-E XT5 110...125V AC/DC	1	piece
1SDA104905R1	MOE-E XT5 220...250V AC/DC	MOE-E XT5 220...250V AC/DC	1	piece
1SDA104907R1	MOE-E XT5 380V AC	MOE-E XT5 380V AC	1	piece
1SDA104826R1	RHD XT5 F/P STAND. DIRECT	RHD XT5 F/P STAND. DIRECT	1	piece
1SDA104827R1	RHD XT5 F/P STAND. DIRECT + 2 PLL	RHD XT5 F/P STAND. DIRECT + 2 PLL	1	piece
1SDA104828R1	RHD XT5 W STAND. DIRECT	RHD XT5 W STAND. DIRECT	1	piece
1SDA104829R1	RHD XT5 W STAND. DIRECT + 2 PLL	RHD XT5 W STAND. DIRECT + 2 PLL	1	piece
1SDA104830R1	RHD_EM XT5 F/P EMER. DIRECT	RHD_EM XT5 F/P EMER. DIRECT	1	piece

1SDA104831R1	RHD_EM XT5 W EMER. DIRECT	RHD_EM XT5 W EMER. DIRECT	1	piece
1SDA104843R1	RHE XT5 F/P STAND. RETURNED	RHE XT5 F/P STAND. RETURNED	1	piece
1SDA104844R1	RHE XT5 W STAND. RETURNED	RHE XT5 W STAND. RETURNED	1	piece
1SDA104845R1	RHE_B XT5 F/P BASE x RETURNED PAD	RHE_B XT5 F/P BASE x RETURNED PAD	1	piece
1SDA104846R1	RHE_B XT5 F/PBASE R.DIST.ADJ.ROT.HA+2PLL	RHE_B XT5 F/PBASE R.DIST.ADJ.ROT.HA+2PLL	1	piece
1SDA104847R1	RHE_B XT5 W BASE x RETURNED PAD	RHE_B XT5 W BASE x RETURNED PAD	1	piece
1SDA104848R1	RHE_B XT5 WBASE R.DIST.ADJ.ROT.HA+2PLL	RHE_B XT5 WBASE R.DIST.ADJ.ROT.HA+2PLL	1	piece
1SDA104849R1	RHE_EM XT5 F EMER. RETURNED	RHE_EM XT5 F EMER. RETURNED	1	piece
1SDA104850R1	RHE_EM XT5 W EMER. RETURNED	RHE_EM XT5 W EMER. RETURNED	1	piece
1SDA104851R1	RHE_H - XT5 F/P/W	RHE_H - XT5 F/P/W	1	piece
1SDA104852R1	RHE_H_EM - XT5 F/P/W	RHE_H_EM - XT5 F/P/W	1	piece
1SDA117351R1	RHE_B XT5 F/P METAL BASE R.DIS.ADJ.ROT.H	RHE_B XT5 F/P METAL BASE R.DIS.ADJ.ROT.H	1	
1SDA113118R1	RHE_S XT5...XT7 F/W 500MM ROD ROT.HAN	RHE_S XT5...XT7 F/W 500MM ROD ROT.HAN	1	piece
1SDA104870R1	KIT for conversion RHE in RHS XT5	KIT for conversion RHE in RHS XT5	1	piece
1SDA101981R1	UVD XT5-XT6 110..125Va.c./d.c.	UVD XT5-XT6 110..125Va.c./d.c.	1	piece
1SDA101982R1	UVD XT5-XT6 220..250Va.c./d.c.	UVD XT5-XT6 220..250Va.c./d.c.	1	piece
1SDA101983R1	UVD XT5-XT6 24..30Va.c./d.c.	UVD XT5-XT6 24..30Va.c./d.c.	1	piece
1SDA101984R1	UVD XT5-XT6 48..60Va.c./d.c.	UVD XT5-XT6 48..60Va.c./d.c.	1	piece
1SDA104924R1	YO XT5-XT6 12 Vdc	YO XT5-XT6 12 Vdc	1	piece
1SDA104925R1	YO XT5-XT6 24...60 Vac/dc	YO XT5-XT6 24...60 Vac/dc	1	piece
1SDA104926R1	YO XT5-XT6 110..240 Vac - 110..250 Vdc	YO XT5-XT6 110..240 Vac - 110..250 Vdc	1	piece
1SDA104927R1	YO XT5-XT6 380...440 Vac	YO XT5-XT6 380...440 Vac	1	piece
1SDA104928R1	YO-C XT5 W 12 Vdc	YO-C XT5 W 12 Vdc	1	piece
1SDA104929R1	YO-C XT5 W24...60 Vac/dc	YO-C XT5 W24...60 Vac/dc	1	piece
1SDA104930R1	YO-C XT5 W 110..240 Vac - 110..250 Vdc	YO-C XT5 W 110..240 Vac - 110..250 Vdc	1	piece
1SDA104931R1	YO-C XT5 W 380...440 Vac	YO-C XT5 W 380...440 Vac	1	piece
1SDA104932R1	YO-C XT5-XT6 F/P 12 Vdc	YO-C XT5-XT6 F/P 12 Vdc	1	piece
1SDA104933R1	YO-C XT5-XT6 F/P 24...60 Vac/dc	YO-C XT5-XT6 F/P 24...60 Vac/dc	1	piece
1SDA104934R1	YO-C XT5-XT6 F/P 110..240Vac-110..250Vdc	YO-C XT5-XT6 F/P 110..240Vac-110..250Vdc	1	piece
1SDA104935R1	YO-C XT5-XT6 F/P 380...440 Vac	YO-C XT5-XT6 F/P 380...440 Vac	1	piece

1SDA119523R1	YO XT5-XT6 72 Vdc SPEC.VERS.	YO XT5-XT6 72 Vdc SPEC.VERS.	1	piece
1SDA104940R1	YU XT5-XT6 12 Vdc	YU XT5-XT6 12 Vdc	1	piece
1SDA104941R1	YU XT5-XT6 24...30 Vac/dc	YU XT5-XT6 24...30 Vac/dc	1	piece
1SDA104942R1	YU XT5-XT6 48...60 Vac/dc	YU XT5-XT6 48...60 Vac/dc	1	piece
1SDA104943R1	YU XT5-XT6 110..127 Vac - 110..125 Vdc	YU XT5-XT6 110..127 Vac - 110..125 Vdc	1	piece
1SDA104944R1	YU XT5-XT6 220..240 Vac - 220..250 Vdc	YU XT5-XT6 220..240 Vac - 220..250 Vdc	1	piece
1SDA104945R1	YU XT5-XT6 380...440 Vac	YU XT5-XT6 380...440 Vac	1	piece
1SDA104947R1	YU-C XT5 W 12 Vdc	YU-C XT5 W 12 Vdc	1	piece
1SDA104948R1	YU-C XT5 W 24...30 Vac/dc	YU-C XT5 W 24...30 Vac/dc	1	piece
1SDA104949R1	YU-C XT5 W 48...60 Vac/dc	YU-C XT5 W 48...60 Vac/dc	1	piece
1SDA104950R1	YU-C XT5 W 110..127 Vac - 110..125 Vdc	YU-C XT5 W 110..127 Vac - 110..125 Vdc	1	piece
1SDA104951R1	YU-C XT5 W 220..240 Vac - 220..250 Vdc	YU-C XT5 W 220..240 Vac - 220..250 Vdc	1	piece
1SDA104952R1	YU-C XT5 W 380...440 Vac	YU-C XT5 W 380...440 Vac	1	piece
1SDA104954R1	YU-C XT5-XT6 F/P 12 Vdc	YU-C XT5-XT6 F/P 12 Vdc	1	piece
1SDA104955R1	YU-C XT5-XT6 F/P 24...30 Vac/dc	YU-C XT5-XT6 F/P 24...30 Vac/dc	1	piece
1SDA104956R1	YU-C XT5-XT6 F/P 48...60 Vac/dc	YU-C XT5-XT6 F/P 48...60 Vac/dc	1	piece
1SDA104957R1	YU-C XT5-XT6 F/P 110..127Vac-110..125Vdc	YU-C XT5-XT6 F/P 110..127Vac-110..125Vdc	1	piece
1SDA104958R1	YU-C XT5-XT6 F/P 220..240Vac-220..250Vdc	YU-C XT5-XT6 F/P 220..240Vac-220..250Vdc	1	piece
1SDA104959R1	YU-C XT5-XT6 F/P 380...440 Vac	YU-C XT5-XT6 F/P 380...440 Vac	1	piece
1SDA105098R1	PLL XT5 PADLOCKS DEVICE OP/CL	PLL XT5 PADLOCKS DEVICE OP/CL	1	piece
1SDA105099R1	PLL XT5 PADLOCKS DEVICE OPEN	PLL XT5 PADLOCKS DEVICE OPEN	1	piece
1SDA105100R1	PLL XT5 REM.PADLOCKS DEVICE OPEN	PLL XT5 REM.PADLOCKS DEVICE OPEN	1	piece
1SDA105092R1	MOL-D XT5-XT6 KE.LO. RONIS SEV.1228xMOE	MOL-D XT5-XT6 KE.LO. RONIS SEV.1228xMOE	1	piece
1SDA105093R1	MOL-M XT5-XT6 KEY LOCK RONIS SEV. x MOE	MOL-M XT5-XT6 KEY LOCK RONIS SEV. x MOE	1	piece
1SDA105094R1	MOL-S XT5-XT6 KE.LO. RONIS EQ.A 1228xMOE	MOL-S XT5-XT6 KE.LO. RONIS EQ.A 1228xMOE	1	piece
1SDA105095R1	MOL-S XT5-XT6 KE.LO. RONIS EQ.B 1228xMOE	MOL-S XT5-XT6 KE.LO. RONIS EQ.B 1228xMOE	1	piece
1SDA105096R1	MOL-S XT5-XT6 KE.LO. RONIS EQ.C 1228xMOE	MOL-S XT5-XT6 KE.LO. RONIS EQ.C 1228xMOE	1	piece
1SDA105097R1	MOL-S XT5-XT6 KE.LO. RONIS EQ.D 1228xMOE	MOL-S XT5-XT6 KE.LO. RONIS EQ.D 1228xMOE	1	piece
1SDA104706R1	KIT FP XT5 W <FP P	KIT FP XT5 W <FP P	1	piece
1SDA105199R1	EKIP Maintenance Module XT5 INT F/P	EKIP Maintenance Module XT5 INT F/P	1	piece

1SDA105200R1	EKIP Maintenance Module XT5 INT W	EKIP Maintenance Module XT5 INT W	1	piece
1SDA105207R1	Connection Kit 24Vdc/Internal Bus XT5 W	Connection Kit 24Vdc/Internal Bus XT5 W	1	piece
1SDA107391R1	Kit external neutral volt. conn XT5 F/P	Kit external neutral volt. conn XT5 F/P	1	piece
1SDA107393R1	Kit Ext NE C+V sensor XT5 Ekip Touch P/W	Kit Ext NE C+V sensor XT5 Ekip Touch P/W	1	piece
1SDA107394R1	Kit Ext NE C sensor XT5 Ekip Touch P/W	Kit Ext NE C sensor XT5 Ekip Touch P/W	1	piece
1SDA107395R1	Kit Ext NE V sensor XT5 Ekip Touch P/W	Kit Ext NE V sensor XT5 Ekip Touch P/W	1	piece
1SDA107396R1	Kit Ext NE sensor XT5 Ekip Dip P/W	Kit Ext NE sensor XT5 Ekip Dip P/W	1	piece
1SDA107397R1	Kit zone selectivity XT5 Ekip Touch P/W	Kit zone selectivity XT5 Ekip Touch P/W	1	piece
1SDA113125R1	Kit zone selectivity XT5 Ekip Touch F	Kit zone selectivity XT5 Ekip Touch F	1	piece
1SDA105148R1	Transparent cover for XT5 Ekip Dip	Transparent cover for XT5 Ekip Dip	1	piece
1SDA105161R1	EKIP COM HUB XT5 INT	EKIP COM HUB XT5 INT	1	piece
1SDA105185R1	EKIP COM ETHERNET/IP XT5 INT	EKIP COM ETHERNET/IP XT5 INT	1	piece
1SDA105186R1	EKIP COM IEC61850 XT5 INT	EKIP COM IEC61850 XT5 INT	1	piece
1SDA105187R1	EKIP COM MODBUS RS-485 XT5 INT F/P	EKIP COM MODBUS RS-485 XT5 INT F/P	1	piece
1SDA105188R1	EKIP COM MODBUS RS-485 XT5 INT W	EKIP COM MODBUS RS-485 XT5 INT W	1	piece
1SDA105189R1	EKIP COM MODBUS TCP XT5 INT	EKIP COM MODBUS TCP XT5 INT	1	piece
1SDA105192R1	EKIP COM PROFINET XT5 INT	EKIP COM PROFINET XT5 INT	1	piece
1SDA105193R1	EKIP COM STA MODBUS RS-485 XT5 INT F/P	EKIP COM STA MODBUS RS-485 XT5 INT F/P	1	piece
1SDA105194R1	EKIP COM STA MODBUS RS-485 XT5 INT W	EKIP COM STA MODBUS RS-485 XT5 INT W	1	piece
1SDA105195R1	EKIP COM STA MODBUS TCP XT5 INT F/P	EKIP COM STA MODBUS TCP XT5 INT F/P	1	piece
1SDA105196R1	EKIP COM STA MODBUS TCP XT5 INT W	EKIP COM STA MODBUS TCP XT5 INT W	1	piece
1SDA105198R1	EKIP LINK XT5 INT	EKIP LINK XT5 INT	1	piece

Categories

Products > Low Voltage Products and Systems > Circuit Breakers > Moulded Case Circuit Breakers > Tmax XT

