



PRODUCT-DETAILS

XT5N 630 Ekip Dip LS/I In=630 3p F F

XT5N 630 Ekip Dip LS/I In=630 3p F F



General Information	
Extended Product Type:	XT5N 630 Ekip Dip LS/I In=630 3p F F
Product ID:	1SDA100355R1
EAN:	8056221004329
Catalog Description:	XT5N 630 Ekip Dip LS/I In=630 3p F F
Long Description:	C.BREAKER TMAX XT5N 630 FIXED THREE-POLE WITH FRONT TERMINALS AND SOLID-STATE RELEASE IN AC EKIP DIP LS/I R 630
Display Name:	XT5N 630 Ekip Dip LS/I In=630 3p F F

ABB EcoSolutions	
ABB EcoSolutions:	Yes
ABB Site Meeting Group Waste To Landfill Target:	UL 2799 Zero Waste To Landfill Validation available
End Of Life Disassembling Instructions:	9AKK108468A2354
Environmental Product Declaration - EPD:	9AKK108468A1899 9AKK108468A9748
Extended Product Lifetime:	Product Modularity

Recyclability Rate of the Product acc. to EN45555: Design for Closing Resource Loops - Standard EN45555 - 61.8 %

Material Compliance

REACH Declaration:	9AKK108466A1425
RoHS Declaration:	9AKK108466A1424
RoHS Information:	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019
Conflict Minerals Reporting Template (CMRT):	9AKK108467A5658
Toxic Substances Control Act - TSCA:	9AKK108467A8326
SCIP:	6adafc8-0b33-43e4-a117-ef0955ee4a96 Italy
Simplified SCIP:	1f62ff8a-3fb4-47fe-a926-11f26235f7b4 Croatia 5ef905ca-6274-404d-b6c8-3751c847a184 Czechia 743a2fd6-594f-479a-84b1-ac0c30f947ac Germany 73e979c2-72c2-48cf-8477-60ff8f411b20 Denmark dbea735a-945a-45fc-acaf-6bea412f42c7 Netherlands ab33c588-67a4-46e3-a9fd-dd6b5e8bb29f Poland e1cef6b9-0044-4e98-ae10-262630c5ae96 Finland 7913fdde-255b-4887-b6e5-b518ef679ebe Belgium 305d24b9-406b-43b0-ab00-ef1a0087a688 Germany ce3bd552-85e7-4501-b770-37d843b75a4d Germany ac4eeb8d-77f1-4273-9618-6cfcc46e37ed Sweden ff8a1585-d2a0-4a10-aa32-e4e633cf6628 France 3d086cf1-bd7e-418b-882f-ed434ffafc23 Sweden 520c3cee-a9ba-4a11-8db6-681e6e0f3877 Poland 8fdbcdda-a6ce-4abe-a89b-d310f133c158 Portugal 39fbdc07-9821-426b-b99b-bd2f73cc38d2 Bulgaria 24e91de3-62af-4888-955b-45e419d70dfe Greece 027c9711-9de1-4788-93ce-ec962119f686 Estonia f93a2911-5f9b-4986-9e0f-e4aa83a92d87 Germany abc47bea-0056-4771-b109-6cc06ea1398a Poland e4011859-e833-42ad-96be-94cbd6b002de Norway 5d2aac3b-3373-4cc3-ae3e-73ecf18f7f9f France 5c70bd0e-e0e5-4589-9f90-179a0e811a00 Hungary 1e77db5e-cf98-4c06-b695-fb4d257c8a9a Germany 0651c51c-8dc5-42d9-b614-5ee3d5321ee0 Spain 4f142d66-e565-47ab-bd32-58cd4b610fc9 Belgium 99086cdd-3b87-4a49-9db7-0c99f98f1fc6 Hungary

Environmental

Environmental Information:	9AKK108467A6707
-----------------------------------	-----------------

Ordering

Order Code US and Canada:	XT5NE363BEFF000XXX
E-Number (Finland):	3641330
E-Number (Norway):	4380250
EAN:	8056221004329
Minimum Order Quantity:	1 piece
Customs Tariff Number:	85362090

Dimensions

Product Net Width:	140 mm
Product Net Height:	205 mm
Product Net Depth / Length:	103.5 mm
Product Net Weight:	4.82 kg

Container Information

Package Level 1 Units:	box 1 piece
Package Level 1 Width:	250 mm
Package Level 1 Height:	245 mm
Package Level 1 Depth / Length:	285 mm
Package Level 1 Gross Weight:	5.308 kg
Package Level 1 EAN:	8056221004329

Additional Information

Circuit Breaker Type to be Associated:	Power Distribution
Product Main Type:	SACE Tmax XT
Product Name:	Moulded Case Circuit Breaker
Product Type:	Automatic Circuit Breaker
Version:	F
CAD Dimensional Drawing:	1SDH002065A1115 1SDH002065A1131

Technical

Current Type:	AC
Electrical Durability:	5000 cycle 60 cycles per hour
Mechanical Durability:	20000 cycle 120 cycles per hour
Number of Poles:	3P
Order Multiple:	1 piece
Power Loss:	45 W
Rated Current (I _n):	630 A
Rated Impulse Withstand Voltage (U _{imp}):	8 kV
Rated Insulation Voltage (U _i):	1000 V
Rated Operational Voltage:	690 V AC

Rated Service Short-Circuit Breaking Capacity (I_{cs}):	(220 V AC) 70 kA (230 V AC) 70 kA (240 V AC) 70 kA (380 V AC) 36 kA (415 V AC) 36 kA (440 V AC) 36 kA (500 V AC) 25 kA (525 V AC) 25 kA (690 V AC) 20 kA
Rated Short-time Withstand Current Low Voltage (I_{cw}):	6 kA
Rated Ultimate Short-Circuit Breaking Capacity (I_{cu}):	(220 V AC) 70 kA (230 V AC) 70 kA (240 V AC) 70 kA (380 V AC) 36 kA (415 V AC) 36 kA (440 V AC) 36 kA (500 V AC) 25 kA (525 V AC) 25 kA (690 V AC) 20 kA
Rated Uninterrupted Current (I_u):	630 A
Release:	Ekip Dip LS/I
Release Type:	EL
Short-Circuit Performance Level:	N
Standards:	IEC60947-2
Sub-type:	XT5
Terminal Connection Type:	Front

Certificates and Declarations

Data Sheet, Technical Information:	1SDC210100D0206 1SDC210099D0206
Declaration of Conformity - CE:	9AKK107680A2824
EU Data Act Compliance Declaration:	1SDH002560A1001
Mechanical Drawings:	1SDH002011A1101
Wiring Diagram:	1SDM000005A1001
Instructions and Manuals:	1SDH002011A1001

External Classifications and Standards

ETIM 9:	EC000228 - Power circuit-breaker for trafo/generator/installation protection
ETIM 10:	EC000228 - Power circuit-breaker for trafo/generator/installation protection
Object Classification Code:	Q
WEEE Category:	5. Small Equipment (No External Dimension More Than 50 cm)
eClass:	V11.1 : 27370409

Accessories

Identifier	Description	Type	Qty	Unit Of Measure
------------	-------------	------	-----	-----------------

1SDA104821R1	AUE XT5-XT6 F/P 2 CONTACTS IN CH x RHx	AUE XT5-XT6 F/P 2 CONTACTS IN CH x RHx	1	piece
1SDA104822R1	AUE XT5-XT6 W 2 CONTACTS IN CH x RHx	AUE XT5-XT6 W 2 CONTACTS IN CH x RHx	1	piece
1SDA104814R1	AUP BOX for FP XT5	AUP BOX for FP XT5	1	piece
1SDA104784R1	AUX-C 1Q + 1SY 400V AC/DC XT5 F/P	AUX-C 1Q + 1SY 400V AC/DC XT5 F/P	1	piece
1SDA104785R1	AUX-C 1Q + 1SY 400V AC/DC XT5 W	AUX-C 1Q + 1SY 400V AC/DC XT5 W	1	piece
1SDA104786R1	AUX-C 1Q + 1SY L 24V DC XT5 F/P	AUX-C 1Q + 1SY L 24V DC XT5 F/P	1	piece
1SDA104787R1	AUX-C 1Q + 1SY L 250V AC/DC XT5 F/P	AUX-C 1Q + 1SY L 250V AC/DC XT5 F/P	1	piece
1SDA104788R1	AUX-C 1Q+1SY 24VDC XT5-XT6 W	AUX-C 1Q+1SY 24VDC XT5-XT6 W	1	piece
1SDA104789R1	AUX-C 1Q+1SY 250V AC/DC XT5-XT6 W	AUX-C 1Q+1SY 250V AC/DC XT5-XT6 W	1	piece
1SDA104790R1	AUX-C 1S51 24VdC XT5-XT6 W	AUX-C 1S51 24VdC XT5-XT6 W	1	piece
1SDA104791R1	AUX-C 1S51 250V AC/dC XT5-XT6 W	AUX-C 1S51 250V AC/dC XT5-XT6 W	1	piece
1SDA104792R1	AUX-C 1S52 24VdC XT5-XT6 W	AUX-C 1S52 24VdC XT5-XT6 W	1	piece
1SDA104793R1	AUX-C 1S52 250V AC/dC XT5-XT6 W	AUX-C 1S52 250V AC/dC XT5-XT6 W	1	piece
1SDA104794R1	AUX-C 2Q 400V AC/DC XT5 W	AUX-C 2Q 400V AC/DC XT5 W	1	piece
1SDA104795R1	AUX-C 2Q 400V AC/DC XT5 F/P	AUX-C 2Q 400V AC/DC XT5 F/P	1	piece
1SDA104796R1	AUX-C 2Q+1SY 250V AC/CC XT5-XT6 W	AUX-C 2Q+1SY 250V AC/CC XT5-XT6 W	1	piece
1SDA104797R1	AUX-C 3Q+1SY 24VDC XT5-XT6 W	AUX-C 3Q+1SY 24VDC XT5-XT6 W	1	piece
1SDA104798R1	AUX-C 3Q+1SY 250V AC XT5-XT6 W	AUX-C 3Q+1SY 250V AC XT5-XT6 W	1	piece
1SDA104799R1	AUX-C 1S52 24VDC XT5-XT6 F/P	AUX-C 1S52 24VDC XT5-XT6 F/P	1	piece
1SDA104800R1	AUX-C 1S52 250V AC/DC XT5-XT6 F/P	AUX-C 1S52 250V AC/DC XT5-XT6 F/P	1	piece
1SDA104871R1	FLD - XT5 F/P	FLD - XT5 F/P	1	piece
1SDA104872R1	FLD - XT5 W	FLD - XT5 W	1	piece
1SDA105061R1	KLC XT5-XT6 K.L.RONIS SE.O/C1228 xCB	KLC XT5-XT6 K.L.RONIS SE.O/C1228 xCB	1	piece
1SDA105062R1	KLC XT5-XT6 KE.LO. RONIS EQ.A 1228 OPxB	KLC XT5-XT6 KE.LO. RONIS EQ.A 1228 OPxB	1	piece
1SDA105063R1	KLC XT5-XT6 KE.LO. RONIS EQ.B 1228 OPxB	KLC XT5-XT6 KE.LO. RONIS EQ.B 1228 OPxB	1	piece
1SDA105064R1	KLC XT5-XT6 KE.LO. RONIS EQ.C 1228 OPxB	KLC XT5-XT6 KE.LO. RONIS EQ.C 1228 OPxB	1	piece
1SDA105065R1	KLC XT5-XT6 KE.LO. RONIS EQ.D 1228 OPxB	KLC XT5-XT6 KE.LO. RONIS EQ.D 1228 OPxB	1	piece
1SDA105066R1	KLC XT5-XT6 KE.LO. RONIS SE.1228 xCB	KLC XT5-XT6 KE.LO. RONIS SE.1228 xCB	1	piece

1SDA105067R1	KLC-A Key lock open Kirk XT5-XT6	KLC-A Key lock open Kirk XT5-XT6	1	piece
1SDA105068R1	KLC-A Key lock open RONIS 1104 XT5-XT6	KLC-A Key lock open RONIS 1104 XT5-XT6	1	piece
1SDA105069R1	KLC-A Key lock open STI XT5-XT6	KLC-A Key lock open STI XT5-XT6	1	piece
1SDA105109R1	KL-D RONIS FP W XT5-XT6 KEY LO. SEV.1228	KL-D RONIS FP W XT5-XT6 KEY LO. SEV.1228	1	piece
1SDA105112R1	KL-D GIUSSANI FP W XT5- XT6 KEY LO.EQ.	KL-D GIUSSANI FP W XT5- XT6 KEY LO.EQ.	1	piece
1SDA105113R1	KL-S GIUSSANI FP W XT5- XT6 KEY LO.EQ.	KL-S GIUSSANI FP W XT5- XT6 KEY LO.EQ.	1	piece
1SDA105114R1	KL-S RONIS FP W XT5-XT6 KEY LO.EQ.1228 A	KL-S RONIS FP W XT5-XT6 KEY LO.EQ.1228 A	1	piece
1SDA105080R1	RHL XT5-XT6 K.L.RONIS SE.O/C1228 RHx/FLD	RHL XT5-XT6 K.L.RONIS SE.O/C1228 RHx/FLD	1	piece
1SDA105081R1	RHL XT5-XT6 KE.LO. RONIS SE.1228 RHx/FLD	RHL XT5-XT6 KE.LO. RONIS SE.1228 RHx/FLD	1	piece
1SDA105082R1	RHL XT5-XT6K.LO.RONIS EQ.FEL.A1228RHxFLD	RHL XT5-XT6K.LO.RONIS EQ.FEL.A1228RHxFLD	1	piece
1SDA105083R1	RHL XT5-XT6K.LO.RONIS EQ.FEL.B1228RHxFLD	RHL XT5-XT6K.LO.RONIS EQ.FEL.B1228RHxFLD	1	piece
1SDA105084R1	RHL XT5-XT6K.LO.RONIS EQ.FEL.C1228RHxFLD	RHL XT5-XT6K.LO.RONIS EQ.FEL.C1228RHxFLD	1	piece
1SDA105085R1	RHL XT5-XT6K.LO.RONIS EQ.FEL.D1228RHxFLD	RHL XT5-XT6K.LO.RONIS EQ.FEL.D1228RHxFLD	1	piece
1SDA104879R1	MOE XT5 24V DC Auto- Reset	MOE XT5 24V DC Auto- Reset	1	piece
1SDA104881R1	MOE XT5 48...60V DC Auto-Reset	MOE XT5 48...60V DC Auto-Reset	1	piece
1SDA104883R1	MOE XT5 110...125V AC/DC Auto-Reset	MOE XT5 110...125V AC/DC Auto-Reset	1	piece
1SDA104885R1	MOE XT5 220...250V AC/DC Auto-Reset	MOE XT5 220...250V AC/DC Auto-Reset	1	piece
1SDA104887R1	MOE XT5 380V AC Auto- Reset	MOE XT5 380V AC Auto- Reset	1	piece
1SDA104899R1	MOE-E XT5 24V DC	MOE-E XT5 24V DC	1	piece
1SDA104901R1	MOE-E XT5 48...60V DC	MOE-E XT5 48...60V DC	1	piece
1SDA104903R1	MOE-E XT5 110...125V AC/DC	MOE-E XT5 110...125V AC/DC	1	piece
1SDA104905R1	MOE-E XT5 220...250V AC/DC	MOE-E XT5 220...250V AC/DC	1	piece
1SDA104907R1	MOE-E XT5 380V AC	MOE-E XT5 380V AC	1	piece
1SDA104826R1	RHD XT5 F/P STAND. DIRECT	RHD XT5 F/P STAND. DIRECT	1	piece
1SDA104827R1	RHD XT5 F/P STAND. DIRECT + 2 PLL	RHD XT5 F/P STAND. DIRECT + 2 PLL	1	piece
1SDA104828R1	RHD XT5 W STAND. DIRECT	RHD XT5 W STAND. DIRECT	1	piece
1SDA104829R1	RHD XT5 W STAND. DIRECT + 2 PLL	RHD XT5 W STAND. DIRECT + 2 PLL	1	piece
1SDA104830R1	RHD_EM XT5 F/P EMER. DIRECT	RHD_EM XT5 F/P EMER. DIRECT	1	piece

1SDA104831R1	RHD_EM XT5 W EMER. DIRECT	RHD_EM XT5 W EMER. DIRECT	1	piece
1SDA104843R1	RHE XT5 F/P STAND. RETURNED	RHE XT5 F/P STAND. RETURNED	1	piece
1SDA104844R1	RHE XT5 W STAND. RETURNED	RHE XT5 W STAND. RETURNED	1	piece
1SDA104845R1	RHE_B XT5 F/P BASE x RETURNED PAD	RHE_B XT5 F/P BASE x RETURNED PAD	1	piece
1SDA104846R1	RHE_B XT5 F/PBASE R.DIST.ADJ.ROT.HA+2PLL	RHE_B XT5 F/PBASE R.DIST.ADJ.ROT.HA+2PLL	1	piece
1SDA104847R1	RHE_B XT5 W BASE x RETURNED PAD	RHE_B XT5 W BASE x RETURNED PAD	1	piece
1SDA104848R1	RHE_B XT5 WBASE R.DIST.ADJ.ROT.HA+2PLL	RHE_B XT5 WBASE R.DIST.ADJ.ROT.HA+2PLL	1	piece
1SDA104849R1	RHE_EM XT5 F EMER. RETURNED	RHE_EM XT5 F EMER. RETURNED	1	piece
1SDA104850R1	RHE_EM XT5 W EMER. RETURNED	RHE_EM XT5 W EMER. RETURNED	1	piece
1SDA104851R1	RHE_H - XT5 F/P/W	RHE_H - XT5 F/P/W	1	piece
1SDA104852R1	RHE_H_EM - XT5 F/P/W	RHE_H_EM - XT5 F/P/W	1	piece
1SDA117351R1	RHE_B XT5 F/P METAL BASE R.DIS.ADJ.ROT.H	RHE_B XT5 F/P METAL BASE R.DIS.ADJ.ROT.H	1	
1SDA113118R1	RHE_S XT5...XT7 F/W 500MM ROD ROT.HAN	RHE_S XT5...XT7 F/W 500MM ROD ROT.HAN	1	piece
1SDA104870R1	KIT for conversion RHE in RHS XT5	KIT for conversion RHE in RHS XT5	1	piece
1SDA101981R1	UVD XT5-XT6 110..125Va.c./d.c.	UVD XT5-XT6 110..125Va.c./d.c.	1	piece
1SDA101982R1	UVD XT5-XT6 220..250Va.c./d.c.	UVD XT5-XT6 220..250Va.c./d.c.	1	piece
1SDA101983R1	UVD XT5-XT6 24..30Va.c./d.c.	UVD XT5-XT6 24..30Va.c./d.c.	1	piece
1SDA101984R1	UVD XT5-XT6 48..60Va.c./d.c.	UVD XT5-XT6 48..60Va.c./d.c.	1	piece
1SDA104924R1	YO XT5-XT6 12 Vdc	YO XT5-XT6 12 Vdc	1	piece
1SDA104925R1	YO XT5-XT6 24...60 Vac/dc	YO XT5-XT6 24...60 Vac/dc	1	piece
1SDA104926R1	YO XT5-XT6 110..240 Vac - 110..250 Vdc	YO XT5-XT6 110..240 Vac - 110..250 Vdc	1	piece
1SDA104927R1	YO XT5-XT6 380...440 Vac	YO XT5-XT6 380...440 Vac	1	piece
1SDA104928R1	YO-C XT5 W 12 Vdc	YO-C XT5 W 12 Vdc	1	piece
1SDA104929R1	YO-C XT5 W24...60 Vac/dc	YO-C XT5 W24...60 Vac/dc	1	piece
1SDA104930R1	YO-C XT5 W 110..240 Vac - 110..250 Vdc	YO-C XT5 W 110..240 Vac - 110..250 Vdc	1	piece
1SDA104931R1	YO-C XT5 W 380...440 Vac	YO-C XT5 W 380...440 Vac	1	piece
1SDA104932R1	YO-C XT5-XT6 F/P 12 Vdc	YO-C XT5-XT6 F/P 12 Vdc	1	piece
1SDA104933R1	YO-C XT5-XT6 F/P 24...60 Vac/dc	YO-C XT5-XT6 F/P 24...60 Vac/dc	1	piece
1SDA104934R1	YO-C XT5-XT6 F/P 110..240Vac-110..250Vdc	YO-C XT5-XT6 F/P 110..240Vac-110..250Vdc	1	piece
1SDA104935R1	YO-C XT5-XT6 F/P 380...440 Vac	YO-C XT5-XT6 F/P 380...440 Vac	1	piece

1SDA119523R1	YO XT5-XT6 72 Vdc SPEC.VERS.	YO XT5-XT6 72 Vdc SPEC.VERS.	1	piece
1SDA104940R1	YU XT5-XT6 12 Vdc	YU XT5-XT6 12 Vdc	1	piece
1SDA104941R1	YU XT5-XT6 24...30 Vac/dc	YU XT5-XT6 24...30 Vac/dc	1	piece
1SDA104942R1	YU XT5-XT6 48...60 Vac/dc	YU XT5-XT6 48...60 Vac/dc	1	piece
1SDA104943R1	YU XT5-XT6 110..127 Vac - 110..125 Vdc	YU XT5-XT6 110..127 Vac - 110..125 Vdc	1	piece
1SDA104944R1	YU XT5-XT6 220..240 Vac - 220..250 Vdc	YU XT5-XT6 220..240 Vac - 220..250 Vdc	1	piece
1SDA104945R1	YU XT5-XT6 380...440 Vac	YU XT5-XT6 380...440 Vac	1	piece
1SDA104947R1	YU-C XT5 W 12 Vdc	YU-C XT5 W 12 Vdc	1	piece
1SDA104948R1	YU-C XT5 W 24...30 Vac/dc	YU-C XT5 W 24...30 Vac/dc	1	piece
1SDA104949R1	YU-C XT5 W 48...60 Vac/dc	YU-C XT5 W 48...60 Vac/dc	1	piece
1SDA104950R1	YU-C XT5 W 110..127 Vac - 110..125 Vdc	YU-C XT5 W 110..127 Vac - 110..125 Vdc	1	piece
1SDA104951R1	YU-C XT5 W 220..240 Vac - 220..250 Vdc	YU-C XT5 W 220..240 Vac - 220..250 Vdc	1	piece
1SDA104952R1	YU-C XT5 W 380...440 Vac	YU-C XT5 W 380...440 Vac	1	piece
1SDA104954R1	YU-C XT5-XT6 F/P 12 Vdc	YU-C XT5-XT6 F/P 12 Vdc	1	piece
1SDA104955R1	YU-C XT5-XT6 F/P 24...30 Vac/dc	YU-C XT5-XT6 F/P 24...30 Vac/dc	1	piece
1SDA104956R1	YU-C XT5-XT6 F/P 48...60 Vac/dc	YU-C XT5-XT6 F/P 48...60 Vac/dc	1	piece
1SDA104957R1	YU-C XT5-XT6 F/P 110..127Vac-110..125Vdc	YU-C XT5-XT6 F/P 110..127Vac-110..125Vdc	1	piece
1SDA104958R1	YU-C XT5-XT6 F/P 220..240Vac-220..250Vdc	YU-C XT5-XT6 F/P 220..240Vac-220..250Vdc	1	piece
1SDA104959R1	YU-C XT5-XT6 F/P 380...440 Vac	YU-C XT5-XT6 F/P 380...440 Vac	1	piece
1SDA105098R1	PLL XT5 PADLOCKS DEVICE OP/CL	PLL XT5 PADLOCKS DEVICE OP/CL	1	piece
1SDA105099R1	PLL XT5 PADLOCKS DEVICE OPEN	PLL XT5 PADLOCKS DEVICE OPEN	1	piece
1SDA105100R1	PLL XT5 REM.PADLOCKS DEVICE OPEN	PLL XT5 REM.PADLOCKS DEVICE OPEN	1	piece
1SDA105092R1	MOL-D XT5-XT6 KE.LO. RONIS SEV.1228xMOE	MOL-D XT5-XT6 KE.LO. RONIS SEV.1228xMOE	1	piece
1SDA105093R1	MOL-M XT5-XT6 KEY LOCK RONIS SEV. x MOE	MOL-M XT5-XT6 KEY LOCK RONIS SEV. x MOE	1	piece
1SDA105094R1	MOL-S XT5-XT6 KE.LO. RONIS EQ.A 1228xMOE	MOL-S XT5-XT6 KE.LO. RONIS EQ.A 1228xMOE	1	piece
1SDA105095R1	MOL-S XT5-XT6 KE.LO. RONIS EQ.B 1228xMOE	MOL-S XT5-XT6 KE.LO. RONIS EQ.B 1228xMOE	1	piece
1SDA105096R1	MOL-S XT5-XT6 KE.LO. RONIS EQ.C 1228xMOE	MOL-S XT5-XT6 KE.LO. RONIS EQ.C 1228xMOE	1	piece
1SDA105097R1	MOL-S XT5-XT6 KE.LO. RONIS EQ.D 1228xMOE	MOL-S XT5-XT6 KE.LO. RONIS EQ.D 1228xMOE	1	piece
1SDA104706R1	KIT FP XT5 W <FP P	KIT FP XT5 W <FP P	1	piece
1SDA105199R1	EKIP Maintenance Module XT5 INT F/P	EKIP Maintenance Module XT5 INT F/P	1	piece

1SDA105200R1	EKIP Maintenance Module XT5 INT W	EKIP Maintenance Module XT5 INT W	1	piece
1SDA105207R1	Connection Kit 24Vdc/Internal Bus XT5 W	Connection Kit 24Vdc/Internal Bus XT5 W	1	piece
1SDA107391R1	Kit external neutral volt. conn XT5 F/P	Kit external neutral volt. conn XT5 F/P	1	piece
1SDA107393R1	Kit Ext NE C+V sensor XT5 Ekip Touch P/W	Kit Ext NE C+V sensor XT5 Ekip Touch P/W	1	piece
1SDA107394R1	Kit Ext NE C sensor XT5 Ekip Touch P/W	Kit Ext NE C sensor XT5 Ekip Touch P/W	1	piece
1SDA107395R1	Kit Ext NE V sensor XT5 Ekip Touch P/W	Kit Ext NE V sensor XT5 Ekip Touch P/W	1	piece
1SDA107396R1	Kit Ext NE sensor XT5 Ekip Dip P/W	Kit Ext NE sensor XT5 Ekip Dip P/W	1	piece
1SDA107397R1	Kit zone selectivity XT5 Ekip Touch P/W	Kit zone selectivity XT5 Ekip Touch P/W	1	piece
1SDA113125R1	Kit zone selectivity XT5 Ekip Touch F	Kit zone selectivity XT5 Ekip Touch F	1	piece
1SDA105148R1	Transparent cover for XT5 Ekip Dip	Transparent cover for XT5 Ekip Dip	1	piece
1SDA105161R1	EKIP COM HUB XT5 INT	EKIP COM HUB XT5 INT	1	piece
1SDA105185R1	EKIP COM ETHERNET/IP XT5 INT	EKIP COM ETHERNET/IP XT5 INT	1	piece
1SDA105186R1	EKIP COM IEC61850 XT5 INT	EKIP COM IEC61850 XT5 INT	1	piece
1SDA105187R1	EKIP COM MODBUS RS-485 XT5 INT F/P	EKIP COM MODBUS RS-485 XT5 INT F/P	1	piece
1SDA105188R1	EKIP COM MODBUS RS-485 XT5 INT W	EKIP COM MODBUS RS-485 XT5 INT W	1	piece
1SDA105189R1	EKIP COM MODBUS TCP XT5 INT	EKIP COM MODBUS TCP XT5 INT	1	piece
1SDA105192R1	EKIP COM PROFINET XT5 INT	EKIP COM PROFINET XT5 INT	1	piece
1SDA105193R1	EKIP COM STA MODBUS RS-485 XT5 INT F/P	EKIP COM STA MODBUS RS-485 XT5 INT F/P	1	piece
1SDA105194R1	EKIP COM STA MODBUS RS-485 XT5 INT W	EKIP COM STA MODBUS RS-485 XT5 INT W	1	piece
1SDA105195R1	EKIP COM STA MODBUS TCP XT5 INT F/P	EKIP COM STA MODBUS TCP XT5 INT F/P	1	piece
1SDA105196R1	EKIP COM STA MODBUS TCP XT5 INT W	EKIP COM STA MODBUS TCP XT5 INT W	1	piece
1SDA105198R1	EKIP LINK XT5 INT	EKIP LINK XT5 INT	1	piece

Categories

Products > Low Voltage Products and Systems > Circuit Breakers > Moulded Case Circuit Breakers > Tmax XT

